

KIT 9000 DIY Home Automation Kit



- Compatible with Android and iPhone devices With its APP "Siera CleverHome".
- Video, Audio, Alarm, Home Automation.
- Wireless self-installing System.
- 3-steps easy installation by using QR code.
- Total control of your Home through your Smartphone.
- All devices are connected to the PT (Pan & Tilt) camera by Wireless.
- Camera with PT Movement (Pan & Tilt).

DIY Home Automation Kit designed for a total control of your home through mobile devices. Video, Audio, Alarm and Home Automation with only three setup steps by QR code.

- Bidirectional audio (listen and/or speak).
- Thermal motion sensor.
- Wireless Sockets (Turn On/Off: Lights, TV, Air Conditioner, etc).
- Door and Window Wireless magnetic sensors.
- Smoke Wireless Sensor.
- Gas Wireless Sensor (optional).
- Wireless Panic Button (optional).
- Alarm Push function (receive events even if your phone is locked).
- E-mail sending function with snapshot.
- HD Video (Data Saving "Auto quality selection depending on your internet connection").
- Image capture.
- Video and audio recording (Continues, by Event, by Schedule) in SD Card (SD Card optional).
- Security password, guest password.
- Programmable Security zones.
- Alarm activation and deactivation from the smartphone.
- Anti-theft security and simulation of presence functions.

SYSTEM COMPONENTS:

- 1 x ACC 9008 - Wireless PT Camera.
- 2 x ACC 9001 - Wireless power socket.
- 1 x ACC 9002 - Wireless Infrared Sensor.
- 2 x ACC 9004 - Magnetic wireless door/window sensor.
- 1 x ACC 9005 - Wireless smoke sensor.

OPTIONAL:

- ACC 9006, Wireless Water Leak Detector.
- ACC 9007, Wireless Gas Leak Sensor.
- ACC 9009, Panic Button.



KIT 9000

DIY Home Automation Kit



SPECIFICATION

CAMERA HUB

Resolution:	720P (1280x720)
SD Card Record:	Support Max. 32GB
Lens:	3.6mm
Pan/Tilt Angle:	Level: 270° / Tilt: 90°
IR LED Lights:	11 x ø5
Night Vision Distance:	Max 8 meters
WiFi Protocol:	IEEE 802.11b/g/n
Alarm Input:	Max 64 Wireless Sensors 433MHz
Socket Control:	Max 3 Wireless Socket 433MHz
PIR Detection Degree:	110°
PIR Detection Range:	8m Open Air

SOCKET

Supported Load:	230V50HZ // 3680W // 1800W
Distance to the Camera:	d20m Open Air

WIRELESS PIR MOTION DETECTOR

External Adapter:	DC5V
Internal Battery:	2 AAA battery
Distance to the Camera:	20m open air
Installation Height:	2.2m
Detection Range:	6-8 meters
Low Battery Reminder:	Yes
Anti-tamper Function:	Yes
Life of Battery:	One Year

DOOR/WINDOW SENSOR

Operating Voltage:	23A 12V battery
Distance to the Camera:	50m open air
Low Battery Reminder:	Yes
Life of Battery:	One Year

WATER LEAK DETECTOR

Operating Voltage:	23A 12V battery
Distance to the Camera:	50m open air
Life of Battery:	One Year

SMOKE DETECTOR

Working Voltage:	9V 6F22 battery
Sensitivity of Smoke:	Grade 2
Emission Distance:	50m open air
Installation Height:	Ceiling (3-4m)
Life of Battery:	One Year

GAS LEAKAGE DETECTOR

Working Voltage:	EU 230V50HZ UK 230V/50HZ US 120V/60HZ AU/CN 240V/50HZ
Alarm Range:	10% / 23% LEL
Distance to the Camera:	20m Open Air
Atmospheric Pressure:	86 / 106 Kpa
Installation Height:	LNG: CH4 (3-4m) // LPG: CO (1m)

ALL PARTS

Temperature Range:	10° C / 45° C
Humidity Range:	10% / 95%